

**Mundorf Coil CF - Air Core Coils, CFC16, 17mm width copper foil**

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
CFC16	0,10	0.1	34 * 24
CFC16	0.12	0.11	35 * 24
CFC16	0.15	0.12	37 * 24
CFC16	0.18	0.13	38 * 24
CFC16	0.22	0.15	38 * 24
CFC16	0.27	0.16	42 * 24
CFC16	0.33	0.18	44 * 24
CFC16	0.39	0.2	46 * 24
CFC16	0.47	0.23	48 * 24
CFC16	0.56	0.26	50 * 24
CFC16	0.68	0.29	52 * 24
CFC16	0.82	0.31	54 * 24
CFC16	1,0	0.37	57 * 24
CFC16	1.2	0.41	61 * 24
CFC16	1.5	0.47	65 * 24
CFC16	1.8	0.5	68 * 24
CFC16	2,0	0.55	70 * 24
CFC16	2.2	0.59	72 * 24
CFC16	2.7	0.65	77 * 24
CFC16	3,0	0.7	79 * 24
CFC16	3.3	0.74	81 * 24
CFC16	3.9	0.84	85 * 24
CFC16	4.7	0.93	88 * 24
CFC16	5.6	1.05	93 * 24
CFC16	6.8	1.18	100 * 24
CFC16	8.2	1.31	108 * 24
CFC16	10	1.5	115 * 24

**Mundorf Coil CF - Air Core Coils, CFC14, 28mm width copper foil**

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
CFC14	0,10	0.07	36 * 34
CFC14	0.12	0.08	38 * 34
CFC14	0.15	0.09	40 * 34
CFC14	0.18	0.1	41 * 34
CFC14	0.22	0.11	44 * 34
CFC14	0.27	0.12	46 * 34
CFC14	0.33	0.13	48 * 34
CFC14	0.39	0.14	50 * 34
CFC14	0.47	0.16	52 * 34
CFC14	0.56	0.18	54 * 34
CFC14	0.68	0.2	56 * 34
CFC14	0.82	0.22	59 * 34
CFC14	1,0	0.26	62 * 34
CFC14	1.2	0.29	65 * 34

CFC14	1.5	0.33	69 * 34
CFC14	1.8	0.36	72 * 34
CFC14	2,0	0.39	75 * 34
CFC14	2.2	0.41	77 * 34
CFC14	2.7	0.46	82 * 34
CFC14	3,0	0.48	84 * 34
CFC14	3.3	0.5	85 * 34
CFC14	3.9	0.55	89 * 34
CFC14	4.7	0.62	94 * 34
CFC14	5.6	0.68	99 * 34
CFC14	6.8	0.78	104 * 34
CFC14	8.2	0.86	109 * 34
CFC14	10	0.9	114 * 34
CFC14	12	0.95	119 * 34
CFC14	15	1.2	125 * 34

#### Mundorf Coil CF - Air Core Coils, CFC12, 44mm width copper foil

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
CFC12	0,10	0.05	41 * 52
CFC12	0.12	0.06	42 * 52
CFC12	0.15	0.06	44 * 52
CFC12	0.18	0.07	45 * 52
CFC12	0.22	0.08	47 * 52
CFC12	0.27	0.09	49 * 52
CFC12	0.33	0.1	51 * 52
CFC12	0.39	0.11	53 * 52
CFC12	0.47	0.12	55 * 52
CFC12	0.56	0.14	57 * 52
CFC12	0.68	0.15	60 * 52
CFC12	0.82	0.17	64 * 52
CFC12	1,0	0.19	67 * 52
CFC12	1.2	0.21	70 * 52
CFC12	1.5	0.24	74 * 52
CFC12	1.8	0.26	78 * 52
CFC12	2,0	0.28	80 * 52
CFC12	2.2	0.29	82 * 52
CFC12	2.7	0.32	86 * 52
CFC12	3,0	0.35	88 * 52
CFC12	3.3	0.37	91 * 52
CFC12	3.9	0.39	95 * 52
CFC12	4.7	0.46	100 * 52
CFC12	5.6	0.5	105 * 52
CFC12	6.8	0.56	110 * 52
CFC12	8.2	0.63	117 * 52
CFC12	10	0.72	120 * 52
CFC12	12	0.85	125 * 52
CFC12	15	1.07	132 * 52

**Mundorf Coil CF - Air Core Coils, CFC10, 70mm width copper foil**

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
CFC10	0,10	0.04	43 * 77
CFC10	0.12	0.04	44 * 77
CFC10	0.15	0.05	47 * 77
CFC10	0.18	0.05	48 * 77
CFC10	0.22	0.06	50 * 77
CFC10	0.27	0.06	53 * 77
CFC10	0.33	0.07	56 * 77
CFC10	0.39	0.08	57 * 77
CFC10	0.47	0.09	59 * 77
CFC10	0.56	0.1	62 * 77
CFC10	0.68	0.11	65 * 77
CFC10	0.82	0.12	68 * 77
CFC10	1,0	0.14	71 * 77
CFC10	1.2	0.15	76 * 77
CFC10	1.5	0.17	80 * 77
CFC10	1.8	0.19	83 * 77
CFC10	2,0	0.2	85 * 77
CFC10	2.2	0.21	88 * 77
CFC10	2.7	0.23	91 * 77
CFC10	3,0	0.25	94 * 77
CFC10	3.3	0.27	97 * 77
CFC10	3.9	0.28	104 * 77
CFC10	4.7	0.31	108 * 77
CFC10	5.6	0.36	111 * 77
CFC10	6.8	0.41	121 * 77
CFC10	8.2	0.47	124 * 77
CFC10	10	0.58	128 * 77
CFC10	12	0.69	134 * 77
CFC10	15	0.86	141 * 77