

Mundorf Coil Drum-core - H50, wire diameter 0.5mm

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
H50	4.7	1.03	26 * 25
H50	5.6	1.14	26 * 25
H50	6.8	1.31	26 * 25
H50	8.2	1.44	26 * 25
H50	10	1.75	35 * 25
H50	12	2.01	35 * 25
H50	15	2.32	35 * 25
H50	18	2.53	35 * 25
H50	22	2.98	35 * 25
H50	27	3.45	35 * 25

Mundorf Coil Drum-core - H71, wire diameter 0.71mm

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
H71	1,0	0.22	26 * 25
H71	1.2	0.25	26 * 25
H71	1.5	0.29	26 * 25
H71	1.8	0.33	26 * 25
H71	2,0	0.35	26 * 25
H71	2.2	0.37	26 * 25
H71	2.7	0.43	26 * 25
H71	3,0	0.46	26 * 25
H71	3.3	0.5	26 * 25
H71	3.9	0.58	26 * 25
H71	4.7	0.66	35 * 25
H71	5.6	0.75	35 * 25
H71	6.8	0.85	35 * 25
H71	8.2	0.96	35 * 25
H71	10	0.87	40 * 38
H71	12	0.98	40 * 38
H71	15	1.12	40 * 38
H71	18	1.28	40 * 38
H71	22	1.49	40 * 38
H71	27	1.68	40 * 38
H71	33	1.93	40 * 38

Mundorf Coil Drum-core - BH71, wire diameter 0.71mm, baked varnished

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
BH71	1,0	0.22	26 * 25
BH71	1.2	0.25	26 * 25
BH71	1.5	0.29	26 * 25
BH71	1.8	0.33	26 * 25
BH71	2,0	0.35	26 * 25
BH71	2.2	0.37	26 * 25

BH71	2.7	0.43	26 * 25
BH71	3,0	0.46	26 * 25
BH71	3.3	0.5	26 * 25
BH71	3.9	0.58	26 * 25
BH71	4.7	0.66	35 * 25
BH71	5.6	0.75	35 * 25
BH71	6.8	0.85	35 * 25
BH71	8.2	0.96	35 * 25
BH71	10	0.87	40 * 38
BH71	12	0.98	40 * 38
BH71	15	1.12	40 * 38
BH71	18	1.28	40 * 38
BH71	22	1.49	40 * 38
BH71	27	1.68	40 * 38
BH71	33	1.93	40 * 38

Mundorf Coil Drum-core - H100, wire diameter 1mm

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
H100	1,0	0.15	26 * 25
H100	1.2	0.18	35 * 25
H100	1.5	0.2	35 * 25
H100	1.8	0.23	35 * 25
H100	2,0	0.2	40 * 38
H100	2.2	0.21	40 * 38
H100	2.7	0.24	40 * 38
H100	3,0	0.25	40 * 38
H100	3.3	0.27	40 * 38
H100	3.9	0.3	40 * 38
H100	4.7	0.34	40 * 38
H100	5.6	0.39	40 * 38
H100	6.8	0.46	40 * 38
H100	8.2	0.54	40 * 38
H100	10	0.64	56 * 35
H100	12	0.71	56 * 35
H100	15	0.82	56 * 35

Mundorf Coil Drum-core - BH100, wire diameter 1mm, baked varnished

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
BH100	1,0	0.15	26 * 25
BH100	1.2	0.18	35 * 25
BH100	1.5	0.2	35 * 25
BH100	1.8	0.23	35 * 25
BH100	2,0	0.2	40 * 38
BH100	2.2	0.21	40 * 38
BH100	2.7	0.24	40 * 38
BH100	3,0	0.25	40 * 38
BH100	3.3	0.27	40 * 38

BH100	3.9	0.3	40 * 38
BH100	4.7	0.34	40 * 38
BH100	5.6	0.39	40 * 38
BH100	6.8	0.46	40 * 38
BH100	8.2	0.54	40 * 38
BH100	10	0.64	56 * 35
BH100	12	0.71	56 * 35
BH100	15	0.82	56 * 35

Mundorf Coil Drum-core - H112, wire diameter 1.12mm

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
H112	8,2	0.47	56 * 35

Mundorf Coil Drum-core - BH112, wire diameter 1.12mm, baked varnished

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
BH112	8,2	0.47	56 * 35

Mundorf Coil Drum-core - H125, wire diameter 1.25mm

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
H125	2.7	0.19	40 * 38
H125	3,0	0.2	40 * 38
H125	3.3	0.21	40 * 38
H125	3.9	0.24	40 * 38
H125	4.7	0.27	40 * 38
H125	5.6	0.33	56 * 35
H125	6.8	0.39	56 * 35

Mundorf Coil Drum-core - BH125, wire diameter 1.25mm, baked varnished

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
BH125	2.7	0.19	40 * 38
BH125	3,0	0.2	40 * 38
BH125	3.3	0.21	40 * 38
BH125	3.9	0.24	40 * 38
BH125	4.7	0.27	40 * 38
BH125	5.6	0.33	56 * 35
BH125	6.8	0.39	56 * 35

Mundorf Coil Drum-core - H132, wire diameter 1.32mm

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
H132	5,6	0.31	56 * 35

Mundorf Coil Drum-core - BH132, wire diameter 1.32mm, baked varnished

Inductor Type	inductance (mH)	DCR (ohm)	dia. * height (mm)
BH132	5,6	0.31	56 * 35